



Standard Features		
MODEL	GB-P45	
Standby Power(50Hz)	40KW/50KVA	
Prime Power(50Hz)	36KW/45KVA	
Engine	PERKINS 1103A-33TG1	
Alternator	STAFMORD PI144K	

• Engine(PERKINS UK 1103A-33TG1)

- Radiator 50°C max, fans are driven by belt, with safety guard
- 24V charge alternator
- Alternator(STAMFORD PI144K),
- single bearing alternator, Protection Class IP23, insulation class H/H
- Dry Type air filter, fuel filter, oil filter, pre-filter, absorber
- Main line circuit breaker
- Standard control panel
- Two12V batteries, rack and cable
- Ripple flex exhaust pipe, Exhaust siphon, flange, muffler
- Operation manual



Generator Set Ratings						
Voltage	Frequency	Phase	P.F (COS⊄)	Standby Amps	Standby Ratings (KW/KVA)	Prime Ratings (KW/KVA)
440/254	50	3	0.8	65.7	40/50	36/45
415/240	50	3	0.8	69.6	40/50	36/45
400/230	50	3	0.8	72.2	40/50	36/45
380/220	50	3	0.8	76	40/50	36/45

Prime Power(PRP):Prime power is available for an unlimited number of annual hours in variable load application, in accordance with GB/T2820-97(eqvISO8528);A10%voerload capability is available for a period of 1 hour within a 12-hour period of operation. Standby Power Rating (ESP):The standby power rating is applicable for supplying emergency





Dimension Of Generator Set		
Dimension(L*W*H)/CM For Open Type	175×75×125 CM	
Net Weight/KG For Open Type	750KGS	
Dimension(L*W*H)/CM For Sound Proof Type	260×100×157 CM	
Net Weight/KG For Sound Proof Type	1300KGS	
Dimension (L*W*H)/MM For Trailer Type		
Net Weight/KG For Trailer Type		

	Specification	Of Engine
	Engine Model	1103A-33TG1
	Manufacturer	PERKINS UK
	Emissions statement	EU2007(EU97/68/EC Stage II)
		EPA Tier 4Final(EPA 40 CFR Part 1039 Tier 4)
	Prime Power	41.5KW/55.6HP
	Standby Power	45.6KW/61.1HP
	Engine Configuration	3Cylinder In Line, 4Stroke, Direct Injection
	Gas Feeding Model	Turbocharged
Engine	Bore×Stroke	105×127 (MM)
	Displacement	3.3L
	Rated Speed	1500RPM
	Speed Governor	Electrical
	Starter Model	12V DC Start
	Fuel Consumption Prime	10.3L/H
	Power (100% load)	
	Totally lubrication system	7.9L
	Capacity	
	Coolant capacity	10.2L
	Cooling System	Water Cool
	Compression Ratio	17.25:1





	Specification C	Of Alternator
	Alternator Model	PI144K
	Manufacturer	STAFMORD company
	Prime Output	36KW/45KVA
	Standby Output	40KW/50KVA
	Excitation Model	Brushless, Self-Exciting
	Cooling Method	Air Cooling
	Connection Type	3 Phase and 12 Wires "Star" Connection
	Power Factor	0.8
	Protection Class	IP23
	Insulation Class	н
	Altitude	≤1000m
	Voltage Regulation,	<±1%
	Steady State	
	Telephone	<50
Alternator	Influence Factor	
	Sudden Voltage Warp	≤±1%
	(100% Sudden Reduce)	
	Sudden Voltage Warp	$\leq \pm 25\%$
	(Sudden Increase)	
	Voltage Stable Time	≤6S
	(100% Sudden Reduce)	
	Voltage Stable Time	≪6S
	(Sudden Increase)	
	Frequency Reduce	0-5% adjustable
	Frequency Regulation,	≤1.5%
	Stead State	
	Frequency Waving	≪0.8%
	Sudden Frequency Warp	≤+12%
	(100% Sudden Reduce)	
	Sudden Frequency Warp	≪-10%
	(100% Sudden Increase)	
	Frequency Recovery Time	≤5S
	(100% Sudden Reduce)	
	Frequency Recovery Time	≤5S
	(Sudden Increase)	
Compliance	GB755,BS5000,VDE0530,NE	MAMG1-22,IED34-1,CSA22.2 and AS1359
Stands		



BPerkins[®]



Control Panel System

DEEPSEA 501K CONTROL MODEL/ MANUAL

With Four Protection

- 1.High water Temperature Shutdown
- 2. Low Oil Pressure Shutdown
- 3. Over Speed Shutdown 4. Over Crank Shutdown
- 5. Protection as Emergent Stop

Parameters of Operation:

- 1. Emergency Stop Button 2.Voltmeter and Selector Switch
- 3. Ammeter and Selector Switch 4. Frequency Meter
- 5. Hour Running Meter6.Alart Buzzer



DEEPSEA 6020 CONTROL MODEL/ MANUAL OR

ATS USE

With Four Protection

- 1. High water Temperature Shutdown
- 2. Low Oil Pressure Shutdown
- 3. Over Speed Shutdown
- 4. Over Crank Shutdown
- 5. Protection as Emergent Stop

Parameters of Operation:

Digital type, all function showed by LED



DEEPSEA 7320 CONTROL MODEL/ MANUAL OR ATS USE

With Four Protection

- 1. High water Temperature Shutdown
- 2. Low Oil Pressure Shutdown
- 3. Over Speed Shutdown
- 4. Over Crank Shutdown
- 5. Protection as Emergent Stop
- 6. With Remote Teleport Communication RS 485
- Parameters of Operation: