

Standard Features

MODEL	GB-C325
Standby Power(50Hz)	286KW/357.5KVA
Prime Power(50Hz)	260KW/325KVA
Engine	Cummins NTA855-G1B
Alternator	STAMFORD HCI444ES

- **Engine(DCEC CumminsNTAA855-G1B)**
- Radiator 40℃ max, fans are driven by belt, with safety guard
- 24V charge alternator
- **Alternator(STAMFORD HCI444ES),**
- single bearing alternator, Protection Class IP22, insulation class H/H
- Dry Type air filter, fuel filter, oil filter, pre-filter, absorber
- Main line circuit breaker
- Standard control panel
- Two12V batteries, rack and cable
- Ripple flex exhaust pipe, Exhaust siphon, flange, muffler
- Operation manual



Generator Set Ratings

Voltage	Frequency	Phase	P.F (COS ϕ)	Standby Amps	Standby Ratings (KW/KVA)	Prime Ratings (KW/KVA)
440/254	50	3	0.8	470	286/357.5	260/320
415/240	50	3	0.8	497	286/357.5	260/320
400/230	50	3	0.8	516	286/357.5	260/320
380/220	50	3	0.8	544	286/357.5	260/320

Prime Power(PRP): Prime power is available for an unlimited number of annual hours in variable load application, in accordance with GB/T2820-97(eqvISO8528); A10% overload capability is available for a period of 1 hour within a 12-hour period of operation.

Standby Power Rating (ESP): The standby power rating is applicable for supplying emergency

Dimension Of Generator Set	
Dimension(L*W*H)/CM For Open Type	302×110×180 CM
Net Weight/KG For Open Type	2950 KG
Dimension(L*W*H)/CM For Sound Proof Type	423×144×220 CM
Net Weight/KG For Sound Proof Type	3800 KG
Dimension (L*W*H)/MM For Trailer Type	
Net Weight/KG For Trailer Type	

Specification Of Engine		
Engine	Engine Model	NTA855–G1B
	Manufacturer	DCEC Cummins
	Prime Power	284KW/380HP
	Standby Power	312.4KW/418.5HP
	Engine Configuration	6Cylinder In Line, 4Stroke,Direct Injection
	Gas Feeding Model	Turbo Charged
	Bore×Stroke	114×135 (MM)
	Displacement	8.9L
	Rated Speed	1500RPM
	Speed Governor	High Precision Electronic Speed Control System
	Starter Model	24V DC Start
	Fuel Consumption Standby Power (110% load)	59L/H
	Fuel Consumption Prime Power (100% load)	53L/H
	Oil Consumption	≤4G/KWH
	Cooling System	Water Cool
	Compression Ratio	16.0:1
	Max Back Pressure	10KPA
	Intake Flow L/S	186M³/MIN
	Exhaust Temperature	470 °C

Specification Of Alternator		
Alternator	Alternator Model	HCI444ES
	Manufacturer	STAMFORD company
	Prime Output	260KW/325KVA
	Standby Output	286KW/357.5KVA
	Excitation Model	Brushless, Self-Exciting
	Cooling Method	Air Cooling
	Connection Type	3 Phase and 12 Wires "Star" Connection
	Power Factor	0.8
	Protection Class	IP22
	Insulation Class	H
	Altitude	$\leq 1000\text{m}$
	Voltage Regulation, Steady State	$\leq \pm 1\%$
	Telephone Influence Factor	< 50
	Sudden Voltage Warp (100% Sudden Reduce)	$\leq \pm 1\%$
	Sudden Voltage Warp (Sudden Increase)	$\leq \pm 25\%$
	Voltage Stable Time (100% Sudden Reduce)	$\leq 6\text{S}$
	Voltage Stable Time (Sudden Increase)	$\leq 6\text{S}$
	Frequency Reduce	0-5% adjustable
	Frequency Regulation, Stead State	$\leq 1.5\%$
	Frequency Waving	$\leq 0.8\%$
	Sudden Frequency Warp (100% Sudden Reduce)	$\leq +12\%$
	Sudden Frequency Warp (100% Sudden Increase)	$\leq -10\%$
	Frequency Recovery Time (100% Sudden Reduce)	$\leq 5\text{S}$
	Frequency Recovery Time (Sudden Increase)	$\leq 5\text{S}$
Compliance Standards	GB755, BS5000, VDE0530, NEMAMG1-22, IED34-1, CSA22.2 and AS1359	

Control Panel System



DEEPSEA501K CONTROL MODEL/ MANUAL USE

With Four Protection

1. High water Temperature Shutdown
2. Low Oil Pressure Shutdown
3. Over Speed Shutdown
4. Over Crank Shutdown
5. Protection as Emergent Stop

Parameters of Operation:

1. Emergency Stop Button
2. Voltmeter and Selector Switch
3. Ammeter and Selector Switch
4. Frequency Meter
5. Hour Running Meter
6. Alart Buzzer



DEEPSEA6020 CONTROL MODEL/ MANUAL OR ATS USE

With Four Protection

1. High water Temperature Shutdown
2. Low Oil Pressure Shutdown
3. Over Speed Shutdown
4. Over Crank Shutdown
5. Protection as Emergent Stop

Parameters of Operation:

Digital type, all function showed by LED



DEEPSEA7320 CONTROL MODEL/ MANUAL OR ATS USE

With Four Protection

1. High water Temperature Shutdown
2. Low Oil Pressure Shutdown
3. Over Speed Shutdown
4. Over Crank Shutdown
5. Protection as Emergent Stop
6. With Remote Teleport Communication RS 485

Parameters of Operation:

Digital type, all function showed by LED